

Fingertip Pulse Oximeter



The MedSource Fingertip Pulse Oximeter measures the SpO₂, Pulse Rate and Pulse Bar, and displays results accurately on the LED screen. The Fingertip Pulse Oximeter is also compact and lightweight for on-the-go use.

Item #	Description	U of M
MS-74004	Fingertip Pulse Oximeter	EA

Fingertip Pulse Oximeter Specifications

Features

- High Brightnes LED dsplays, Blood Oxygen Level, Pulse Rate, and Pulse Bar
- Low power consumption; battery-low indicator
- 2 AAA alkaline batteries

Operation Temperature: 41°F ~ 104°F

Storage Temperature: -40°F ~ 140°F

Operation Humidity: 10% ~ 95%

Storage Humidity: 10% ~ 95%

Technical Specifications

SpO2 Measurement Range	70% ~ 100%
SpO2 Measurement Accuracy	70% ~ 100% ± 2%; 0% ~ 69% unspecified
PR Measurement Range	25bpm ~ 250bpm
PR Measurement Accuracy	25bpm ~ 250bpm ± 3bpm Resolution 1bpm